

ADJ ENCORE PROFILE PRO WW DMX TRAITS

Modes			DMX	Function
Basic	Standard	Extended	Values	
1	1	1	000-255	Dimmer Intensity 8bit 0 to 100%
2	2	2	000-255	Dimmer Fine 16bit
				Shutter
			000-031	Shutter Closed (LEDs OFF)
			032-063	Shutter OPEN (LEDs ON)
			064-095	Strobe effect slow to fast
			096-127	Shutter OPEN (LEDs ON)
			128-159	Pulse effect in sequences
			160-191	Shutter OPEN (LEDs ON)
			192-223	Random strobe effect slow to fast
			224-255	Shutter OPEN (LEDs ON)
			248-255	Open
				Dim Modes
			000-020	Standard
			021-040	Stage
			041-060	TV
			061-080	Architectural
			081-100	Theatre
			101-120	Stage 2
				Dimming Speed
			121	0.0 s
			122	0.1 s
			123	0.2 s
			124	0.3 s
			125	0.4 s
			126	0.5 s
			127	0.6 s
			128	0.7 s
			129	0.8 s
			130	0.9 s
			131	1 s
			132	1.5 s
			133	2 s
			134	3 s
			135	4 s
			136	5 s
			137	6 s
			138	7 s
			139	8 s
			140	9 s
			141	10 s
			142-255	Default to Unit Setting
				Dim Curves
			000-020	Linear
			021-040	Square
			041-060	Inv. Squa
			061-080	S. Curve
			081-255	No Function

Modes		DMX	Function
Basic	Standard	Extended	Values
			LED Refresh Rates
			029-029 1080 Hz LED Refresh Rate
			030-030 1090 Hz LED Refresh Rate
			031-031 1100 Hz LED Refresh Rate
			032-032 1110 Hz LED Refresh Rate
			033-033 1120 Hz LED Refresh Rate
			034-034 1130 Hz LED Refresh Rate
			035-035 1140 Hz LED Refresh Rate
			036-036 1150 Hz LED Refresh Rate
			037-037 1160 Hz LED Refresh Rate
			038-038 1170 Hz LED Refresh Rate
			039-039 1180 Hz LED Refresh Rate
			040-040 1190 Hz LED Refresh Rate
			041-041 1210 Hz LED Refresh Rate
			042-042 1220 Hz LED Refresh Rate
			043-043 1230 Hz LED Refresh Rate
			044-044 1240 Hz LED Refresh Rate
			045-045 1250 Hz LED Refresh Rate
			046-046 1260 Hz LED Refresh Rate
			047-047 1270 Hz LED Refresh Rate
			048-048 1280 Hz LED Refresh Rate
			049-049 1290 Hz LED Refresh Rate
			050-050 1300 Hz LED Refresh Rate
			051-051 1310 Hz LED Refresh Rate
			052-052 1320 Hz LED Refresh Rate
			053-053 1330 Hz LED Refresh Rate
		6	054-054 1340 Hz LED Refresh Rate
			055-055 1350 Hz LED Refresh Rate
			056-056 1360 Hz LED Refresh Rate
			057-057 1370 Hz LED Refresh Rate
			058-058 1380 Hz LED Refresh Rate
			059-059 1390 Hz LED Refresh Rate
			060-060 1400 Hz LED Refresh Rate
			061-061 1410 Hz LED Refresh Rate
			062-062 1420 Hz LED Refresh Rate
			063-063 1430 Hz LED Refresh Rate
			064-064 1440 Hz LED Refresh Rate
			065-065 1450 Hz LED Refresh Rate
			066-066 1460 Hz LED Refresh Rate
			067-067 1470 Hz LED Refresh Rate
			068-068 1480 Hz LED Refresh Rate
			069-069 1490 Hz LED Refresh Rate
			070-070 1500 Hz LED Refresh Rate
			071-071 2500 Hz LED Refresh Rate
			072-072 4000 Hz LED Refresh Rate
			073-073 5000 Hz LED Refresh Rate
			074-074 6000 Hz LED Refresh Rate
			075-075 10K Hz LED Refresh Rate
			076-076 15K Hz LED Refresh Rate
			077-077 20K Hz LED Refresh Rate
			078-078 25K Hz LED Refresh Rate
			079-079 Disable LED Refresh Rate
			080-255 No Function