

Quick guide for changing of a pre-configured computer board and a panel board ESP2

IMPORTANT! This instruction shall be used when both the computer board and the panel board shall be changed and when the computer board **has been pre-configured for a specific machine** by Wexiödisk.

Change of a pre-configured computer board and the panel board

1. Start from a machine that is not voltage-fed and make sure that the main switch is turned off. Also make sure that the tanks are empty and doors are opened.
2. Change the computer board and connect all contacts.
3. Change the panel board if it shall be changed and connect the contact J2 alternatively J3. Control once again that the contact has been mounted in the right direction on the computer board.
4. Turn on the main switch and start the machine.
5. Enter service mode and make sure that all nominal values are right. Check in particular the nominal settings MACHINE TYPE. Leave the service mode.
6. Test the machine and check that the machine works as you wish. Also check the functionality of any extra equipment that may be activated.

Important

Use the enclosed wristband to protect the boards from electrostatic discharge when you change the board.

For warranty service, return replaced boards immediately, in the packing that the new boards came in together with the stub below completed with information. Use this address:
Returgods, Wexiödisk AB, Mårdvägen 4, 352 45 VÄXJÖ, Sweden.

.....

Order number:..... Date:.....

Board number on the old board (CPU):

Machine number:..... Machine type:

Changed by (name and phone number):.....

Error symptom:.....

.....

.....

.....

.....

.....

.....