

Aidalarm – Battery Powered Disabled Toilet Alarm Kit

A600LKITB

This battery powered kit meets the requirements for emergency signalling systems for disabled persons. It is fully compliant with BS8300 and the Disability Discrimination Act. Everything is provided in the kit to deliver an effective, fully compliant, simple to install and simple to use system.

The system is entirely battery powered and as such avoids any conflict with Part P building regulations.

How the Aidalarm Works

- The Aidalarm controller should be sited where staff are located who can respond to an emergency call.
- Ceiling pull cord and optional Dado panic strip or call button are situated in the toilet or other area where assistance may be required.
- Pulling the cord or pressing the panic strip/call button generates an immediate audible/visual alarm at both the WC and at the control panel. An LED illuminates on the pull cord giving the caller reassurance the call has been placed.
- The call can be silenced by pressing the button on the front of the control panel.
- The audible indicators at the WC will bleep every 5 seconds to re-assure the caller.
- Should the cord be pulled again while in the silenced state, the system will call again.
- Non-attendance will cause the panel to bleep every 40 seconds as a warning.
- The system can only be reset by the Press to Reset button located at or near the point of call.

Features and Benefits

- DDA & BS8300 Compliant
- Controller with High Power Piezo Sounder
- Four selectable Warning Tones
- Powered by 6 AA Alkaline batteries
- Low Battery Warning
- Audible & Visual Signalling to remote point
- Ceiling Pull Cord with LED
- Pull Cord Instruction Label with Braille
- Reset Button with LED, Sounder & Braille
- Overdoor Audible Visual Indication
- Optional Dado Panic Strip or Call Button can be added to suit requirements
- Mains powered version available
- Manufactured in the UK
- UKCA and CE marked, ROHS compliant



A600LKITB Contents

- 1 x A600B battery powered Aidalarm controller
- 1 x S1600-R Pull cord c/w re-assurance LED
- 1 x LAB35107 Pull Cord label with braille
- 1 x S1778A Aidalarm Overdoor light and sounder
- 1 x S1708A Aidalarm Reset button with re-assurance LED, sounder and braille text
- 6 x AA Alkaline batteries

Optional: S1703PYTC customisable button with integral sounder and LEDs

