

**Rated power information for VLP series**

VLP300 (Rated Power: 2x100W@8Ohm,2x150W@4Ohm)

VLP600 (Rated Power: 2x220W@8Ohm,2x300W@4Ohm)

VLP1000 (Rated Power: 2x330W@8Ohm,2x500W@4Ohm)

VLP1500 (Rated Power: 2x500W@8Ohm,2x750W@4Ohm)

VLP2500 (Rated Power: 2x700W@8Ohm,2x1100W@4Ohm)

Model	Switch position	Gain dB / Voltage	Sensitivity		Output	
			8Ohm	4Ohm	8Ohm	4Ohm
VLP300	0.775V	31.5dB / 36.5x	0dBu / 0.775V	-1.5dBu / 0.65V	100W / 28.3V	150W / 24.5V
	1V	29dB / 28.3x	2.2dBu / 1V	1dBu / 0.87V		
	1.44V	25.9dB / 19.6x	5.4dBu / 1.44V	4.1dBu / 1.24V		
VLP600	0.775V	34.7dB / 54.2x	0dBu / 0.775V	-1.7dBu / 0.64V	220W / 42V	300W / 34.6V
	1V	32.5dB / 42x	2.2dBu / 1V	0.5dBu / 0.82V		
	1.44V	29.3dB / 29.2x	5.4dBu / 1.44V	3.7dBu / 1.19V		
VLP1000	0.775V	36.4dB / 66.3x	0dBu / 0.775V	-1.2dBu / 0.68V	330W / 51.4V	500W / 44.7V
	1V	34.2dB / 51.4x	2.2dBu / 1V	1dBu / 0.87V		
	1.44V	31dB / 35.7x	5.4dBu / 1.44V	4.2dBu / 1.26V		
VLP1500	0.775V	38.2dB / 81.5x	0dBu / 0.775V	-1.2dBu / 0.68V	500W / 63.2V	750W / 54.8V
	1V	36dB / 63.2x	2.2dBu / 1V	1dBu / 0.87V		
	1.44V	32.9dB / 43.9x	5.4dBu / 1.44V	4.1dBu / 1.24V		
VLP2500	0.775V	39.7dB / 96.5x	0dBu / 0.775V	-1.1dBu / 0.69V	700W / 74.8V	1100W / 66.3V
	1V	37.5dB / 74.8x	2.2dBu / 1V	1.1dBu / 0.89V		
	1.44V	34.3dB / 51.9x	5.4dBu / 1.44V	4.3dBu / 1.28V		