High-voltage test system T 22/1 High voltage testing up to 75kV_{RMS} AC / 80 kV DC



- Compact and light
- Continuous testing with AC voltages up to 75 kV_{RMS} at 1 kVA
- Expandable with a second transformer for testing up to 150 kV_{RMS}
- Built-in overload protection
- DC testing up to 80 kV with optional rectifier

DESCRIPTION

The High-voltage test system T 22/1 is a portable test set consisting of two separate units: the control unit and the high-voltage unit. This division enables the operator to use the test set on site without transport aids. The test set can be equipped with a rectifier attachment for DC voltage testing up to 80 kV.

The Test Set T 22/1 is used for:

- AC voltage testing of low capacity test objects
 (e. g. metal-enclosed high voltage switchgears)
- DC voltage testing of cable systems and equipment up to 80 kV using a rectifier attachment

The light and compact high-voltage transformer, insulated with insulating gas (SF 6), produces a high voltage of $75\,\text{kV}_{\text{rms}}$. The voltage is continuously adjustable from $0-75\,\text{kV}$ using a regulating transformer.

In the basic version for AC voltage testing, the output voltage is calculated and indicated by measuring the primary voltage of the high-voltage transformer and converted using the turn factor (M 402 measuring unit).

Alternatively, the voltage can be measured on high-voltage potential cables by using a measuring resistor and the M 402/1 unit.

DC voltage can be generated using the optional rectifier attachment. The voltage is then measured by using a separate measuring resistor and the M 401 measuring unit.

TECHNICAL DATA*

T 22/1

 $\begin{array}{lll} \textbf{Power consumption P}_{\textbf{N}} & 1 \text{ kVA} \\ \textbf{Power consumption} & 4 \text{ kVA} \\ \end{array}$

short-time P_K (1 min)

Input voltage 230 V / 50 ... 60 Hz

Output voltage 0 ... 75 kV_{RMS} (basic version)

0 ... 150 kV $_{\rm RMS}$ (upgrade version 150 kV $_{\rm RMS}$) 0 ... 80 kV $_{\rm DC}$ (upgrade version 80 kV $_{\rm DC}$)

Measuring range 0 ... 80 kV_{RMS} (basic version)

0 ... 60 kV / 0 ... 120 kV_{DC} (upgrade version 80 kV_{DC})

 Precision
 2.5 %

 Output current
 0 ... 13 mA

50 mA maximum (1 min)

Measuring range 0 ... 20 A_{RMS} (basic version),

 $0\,...\,200~\mu\text{A}\,/\,0\,...\,2~m\text{A}\,/\,0\,...\,20~m\text{A}$ DC

(upgrade version 80 kV_{DC})

 $0 \dots 60 \text{ mA}_{\text{RMS}}$ (option current measure-

ment HV potential)

Control unit T 22/124

Weight 19 kg

Dimensions (W x H x D) 551 x 255 x 380 mm

Transformer T 22/12

Weight 29 kg

Dimensions (Ø x H) 420 x 560 mm

FEATURES

- Continuous testing with AC voltages up to 75 kV at 1 kVA
- Separate control and HV-unit
- Built-in overload protection
- DC Voltage testing with optional rectifier attachment

SCOPE OF DELIVERY

- Control Unit
- Transformer
- Set of cables T 22/1 incl. bag
- Filling device
- Secondary current measurement

| ORDERING INFORMATION | |
|-------------------------------------|-------------|
| Product | Order no. |
| T 22/1 High voltage test set | 892502151-S |
| Option: | |
| Upgrade to 80 kV _{DC} | 892504480 |
| Upgrade to 150 kV _{RMS} | 892502152 |
| Voltage measurement on HV-potential | 899000409 |
| Earthing stick 100 kV | 810327 |
| Transport case (offshore) | 90015989 |
| | |

SALES OFFICES

Megger GmbH

Obere Zeil 2
D-61440 Oberursel
Germany
T +49 6171 92987-0

E info@megger.de

Seba Dynatronic Mess- und Ortungstechnik GmbH Dr.-Herbert-lann-Str. 6 96148 Baunach Germany T +49 9544 68-0 E team.international@megger.de T221_DS_EN_V01a

www.megger.com ISO 9001

The word 'Megger' is a registered trademark.



^{*} We reserve the right to make technical changes.