

Supplementary Information

The Large Electrocaloric Effect in Lead-free Ba(Hf_xTi_{1-x})O₃

Ferroelectric Ceramics for Clean Energy Applications

Ming-Ding Li¹, Xin-Gui Tang^{1*}, Si-Ming Zeng², Qiu-Xiang Liu¹, Yan-Ping Jiang¹,

Tian-Fu Zhang¹ and Wen-Hua Li¹

¹ School of Physics & Optoelectric Engineering, Guangdong University of Technology, No 100

Waihuan Xi Road, Guangzhou 510006, China.

² Laboratory Teaching Centre, Guangdong University of Technology, No 100 Waihuan Xi Road,

Guangzhou 510006, China.

*Corresponding author, E-mail: xgtang@gdut.edu.cn (X.G. Tang);

Fax: +86-20-3932 2265

Total number of pages: 4

Total number of figures: 2

Table of Contents

- 1. Experimental section.....S2**
- 2. Figure S1: the pyroelectric coefficient $\partial P/\partial T$ as a function of temperature of BHT.....S3**
- 3. Figure S2: Isothermal entropy change ΔS as a function of temperature of BHT.....S4**

EXPERIMENTAL SECTION

The BHT ($x=0.03, 0.05, 0.08$ and 0.11) ceramics synthesized by a solid-state process. Reagent-grade BaCO_3 , TiO_2 and HfO_2 powders were batched stoichiometrically according to the nominal compositions BHT. Raw powders were ball milled in alcohol for 24 h and dried, followed by calcinations at $1100\text{ }^\circ\text{C}$ for 2 h. The calcined powders were mixed with alcohol milling for 16 h and dried. After that, they were mixed thoroughly with a Polyvinyl butyral (PVB) binder solution and uniaxially pressed into discs of 12 mm in diameter pellet. These discs were sintered at $1450\text{ }^\circ\text{C}$ for 5 h in air. Silver paste was painted on both surfaces of the disc samples and then fired at $650\text{ }^\circ\text{C}$ to form the electrode.

The crystal structures of the sintered ceramics were characterized using X-ray diffraction (XRD, Rigaku ULTIMA-III). The surface microstructure of BHT ceramics were obtained by a scanning electron microscopy (SEM, S-3400N, Hitachi, Japan). Dielectric measurements were performed using a Agilent E4980A in the frequency range from 100 Hz to 1 MHz and in the temperature range from 25 to $600\text{ }^\circ\text{C}$ with a heating rate of $3\text{ }^\circ\text{C}/\text{min}$. P - E loops were obtained by a ferroelectric test system (Premier II, Radiant Technology, USA).




Figure S1. The pyroelectric coefficient $\partial P/\partial T$ as a function of temperature of BHT (a) $x = 0.03$, (b) $x = 0.05$, (c) $x = 0.08$, (d) $x = 0.11$ ceramics at various electric fields.




Figure S2. Isothermal entropy change ΔS as a function of temperature of BHT (a) $x = 0.03$, (b) $x = 0.05$, (c) $x = 0.08$, (d) $x = 0.11$ ceramics at various electric fields.