



HP LaserJet Enterprise MFP M527 series

Finish tasks faster¹ and help protect against threats with multi-level device security.¹⁰

Finish tasks faster with an MFP that starts right away and helps conserve energy.¹ Multi-level device security helps protect from threats.¹⁰ Original HP Toner cartridges with JetIntelligence and this printer produce more high-quality pages.²



HP LaserJet Enterprise MFP M527dn



HP LaserJet Enterprise Flow MFP M527c

Accelerate your work and use less energy

- Don't wait for documents. Print your first page in as few as 8.5 seconds from energy-efficient sleep mode.
- Speed through jobs. Print two-sided documents quickly, and scan both sides of the page at once.
- This MFP leads its class in low energy use—thanks to its innovative design and toner technology.³
- Now 24% smaller—this MFP fits in tight places to boost performance in any workspace.⁹

Unparalleled fleet security and management

- Embedded features detect security threats and heal your MFP, protecting it from boot up to shutdown.¹⁰
- Protect sensitive data on the MFP and in transit, using embedded security features and 256-bit encryption.¹⁰
- Protect sensitive business data with embedded and optional HP JetAdvantage Security Solutions.¹¹
- Centralize control of your printing environment with HP Web Jetadmin¹²—and help build business efficiency.

More. Pages, Performance, and Protection.

- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Get more. Original HP Toner with JetIntelligence delivers more pages per cartridge than predecessors.²
- Help ensure the Original HP quality you paid for with anti-fraud and cartridge authentication technology.
- Print right away with a preinstalled toner cartridge. Replace it with an optional high-yield cartridge.¹³

Stay connected with secure mobile printing options

- Enable 128-bit encrypted wireless direct printing from mobile devices—without accessing the network.⁴
- Print with just a touch of your NFC-enabled mobile device to this printer—no network needed.⁶
- Easily print from a variety of smartphones and tablets—generally no setup or apps required.⁷
- Easily access, print, and share resources with Ethernet and optional wireless networking.⁵

¹ Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details, see <http://www.hp.com/go/Ljclaims>

² More pages versus predecessor cartridges claim based on page-yield comparison of HP 55X High Yield Black Original LaserJet Toner Cartridges with HP 87X High Yield Black Original LaserJet Toner Cartridges. For more information, see <http://www.hp.com/go/learnaboutsupplies>

³ Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov versus the top three leading competitors as of 8/2015. Actual results may vary. For details see <http://www.hp.com/go/Ljclaims>

⁴ Wireless direct printing is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MFP or printer. For details, see <http://www.hp.com/go/businessmobileprinting>

⁵ Wireless networking requires purchase of the HP Jetdirect Z900nw Print Server. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections.

⁶ Touch-to-print capability is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device must support Near Field Communication (NFC)-enabled printing. For more information, see <http://www.hp.com/go/businessmobileprinting>

⁷ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>

⁸ Purchase of optional paper trays required to reach maximum input capacity.

⁹ Compared with the HP LaserJet Enterprise MFP M525.

¹⁰ Only HP offers a combination of security features for integrity checking down to the BIOS with self-healing capabilities. Some features require additional purchase. A FutureSmart service pack update may be required to activate security features. Learn more at <http://www.hp.com/go/printersthatprotect>

¹¹ Some solutions require download or additional purchase. Learn more at <http://www.hp.com/go/printingsolutions>

¹² Universal device plug-in is offered with HP Web Jetadmin 10.3 SR4 and higher. HP Web Jetadmin is free and available for download at <http://www.hp.com/go/webjetadmin>

¹³ HP 87X High Yield Black Original LaserJet Toner Cartridges not included; please purchase separately.

Product walkaround

1. 100-sheet automatic document feeder (ADF) with single-pass, two-sided scanning and HP EveryPage
2. Hardware Integration Pocket (HIP)¹ for connecting accessory and third-party devices
3. 250-sheet output tray
4. Easy-access USB port to save and print files directly²
5. Top cover (access to Original HP Toner cartridges with JetIntelligence)
6. 100-sheet multipurpose tray
7. 550-sheet tray 2
8. Intuitive 8-inch (20.3 cm) touchscreen control panel
9. Pull-out keyboard for easy, accurate data entry
10. Convenience stapler
11. Convenient front on/off button
12. Built-in automatic duplexer
13. Built-in wireless direct³ and NFC touch-to-print⁴
14. 800 MHz processor, 1.5 GB RAM⁵
15. HP High-Performance Secure Hard Disk
16. Slot for optional cable-type security lock
17. Fax port
18. HP Jetdirect Gigabit Ethernet print server
19. Hi-Speed USB 2.0 port (for connecting third party devices)
20. Hi-Speed USB 2.0 printing port
21. Rear door (access to the print path)



Series at a glance



Model	HP LaserJet Enterprise MFP M527dn	HP LaserJet Enterprise Flow MFP M527c
Product number	F2A76A	F2A81A
Fax	Optional	√
HP High-Performance Secure Hard Disk	Optional	√
100-page ADF with single-pass, two sided scanning	√	√ (Plus HP EveryPage)
Advanced workflow capabilities including pull-out keyboard	Not available	√
Wireless direct ³ and NFC touch to print ⁴	Optional	
ENERGY STAR® and Blue Angel certified	√	

HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. HP Care Pack Services provide a comprehensive suite of protection services designed to keep HP hardware and software up and running so employees can stay productive.

For carepack availability visit: hp.com/go/cpc:

Top features

Work quickly with the fastest first page out from sleep mode—on the most energy-efficient MFP in its class.^{1,3} Launch two-sided printing, scan, and fax right from the touchscreen. Reload paper less often with a 2300-sheet maximum capacity.⁸

Trust your MFP is secure from power-up to power-down. Get strong protection for devices, data, and documents with embedded and optional security features while centrally managing your entire fleet.¹⁰

Bring out the best in your MFP. Print more high-quality pages than ever before,² using specially designed Original HP Toner cartridges with JetIntelligence. Count on the authentic HP quality you paid for—something the competition can't match.

Enable secure wireless printing in the office—with or without network access⁴—and keep users connected with Ethernet and optional wireless networking. Print with just a touch from mobile devices.⁵

Accessories

- 2MU47A** HP Accessibility Assistant
- 2NR12A** HP Removable Hard Drive Enclosure
- 2TD64A** HP Accessibility Kit
- B5L29A** HP High-Performance Secure Hard Disk
- B5L31A** HP Foreign Interface Harness
- B5L53A** HP LaserJet MFP Analog Fax Accessory 600
- E5K48A** HP 1 GB x32 144-pin (800 MHz)DDR3 SODIMM
- F2A72A** HP LaserJet 550-sheet Paper Tray
- F2A73A** HP LaserJet Printer Cabinet
- F2A87A** HP Internal USB Ports
- F5562A** HP Trusted Platform Module Accessory
- F8B30A** HP SmartCard SIPRNet Solution for US Government
- J8030A** HP Jetdirect 3000w NFC/Wireless Accessory
- J8031A** HP Jetdirect 2900nw Print Server
- W5U23A** HP 200 ADF Roller Replacement Kit
- 2NR09A** HP 2GB 144-Pin DDR3 TAA Version DIMM
- 3JN69A** HP Jetdirect 3100w BLE/NFC/Wireless Accessory
- B5L28A** HP Internal USB Ports
- E5K49A** HP 2 GB x32 144-pin (800 MHz) DDR3 SODIMM
- Q7432A** HP Staple Cartridge Pack

Supplies

- HP 87A Black Original LaserJet Toner Cartridge (~9000 pages) **CF287A**
- HP 87X Black Original LaserJet Toner Cartridge (~18000 pages) **CF287X**

Services

- U8TT4E** - HP 2 years Next business day + DMR LaserJet M527 MFP HW Support
- U8TT5E** - HP 3 years Next business day + DMR LaserJet M527 MFP HW Support
- U8TT6E** - HP 4 years Next business day + DMR LaserJet M527 MFP HW Support
- U8TT7E** - HP 5 years Next business day + DMR LaserJet M527 MFP HW Support
- U8TV6PE** - HP 1 year Post Warranty Next business day + DMR LaserJet M527 MFP HW Support



¹ Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details, see <http://www.hp.com/go/Ljclaims>

² More pages versus predecessor cartridges claim based on page-yield comparison of HP 55X High Yield Black Original LaserJet Toner Cartridges with HP 87X High Yield Black Original LaserJet Toner Cartridges. For more information, see <http://www.hp.com/go/learnaboutsupplies>

³ Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov versus the top three leading competitors as of 8/2015. Actual results may vary. For details see <http://www.hp.com/go/Ljclaims>

⁴ Wireless direct printing is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MFP or printer. For details, see <http://www.hp.com/go/businessmobileprinting>

⁵ Wireless networking requires purchase of the HP Jetdirect 2900nw Print Server. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections.

⁶ Touch-to-print capability is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device must support Near Field Communication (NFC)-enabled printing. For more information, see <http://www.hp.com/go/businessmobileprinting>

⁷ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>

⁸ Purchase of optional paper trays required to reach maximum input capacity.

⁹ Compared with the HP LaserJet Enterprise MFP M525.

¹⁰ Only HP offers a combination of security features for integrity checking down to the BIOS with self-healing capabilities. Some features require additional purchase. A FutureSmart service pack update may be required to activate security features. Learn more at <http://www.hp.com/go/printersthatprotect>

¹¹ Some solutions require download or additional purchase. Learn more at <http://www.hp.com/go/printingsolutions>

¹² Universal device plug-in is offered with HP Web Jetadmin 10.3 SR4 and higher. HP Web Jetadmin is free and available for download at <http://www.hp.com/go/webjetadmin>

¹³ HP 87X High Yield Black Original LaserJet Toner Cartridges not included; please purchase separately

HP LaserJet Enterprise MFP M527 series

Model	HP LaserJet Enterprise MFP M527dn	HP LaserJet Enterprise Flow MFP M527c
Product number	F2A76A	F2A81A
AIO functions	Print, copy, scan; AIO multitasking supported: Yes	Print, copy, scan, fax; AIO multitasking supported: Yes
Print		
Print speed ^{15, 17, 16}	Letter: Up to 45 ppm Black; 2-sided: Up to 36 ipm Black; First page out: As fast as 5.7 sec.; As fast as 11.2 sec (100 V) Black; Print speed (Landscape, A5): Up to 65 ppm Black	Letter: Up to 45 ppm Black; 2-sided: Up to 36 ipm Black; First page out: As fast as 5.9 sec.; As fast as 11.3 sec (100 V) Black; Print speed (Landscape, A5): Up to 65 ppm Black
Print resolution	Black (best) Up to 1200 x 1200 dpi; Black (normal) Up to 600 x 600 dpi; Black (fine lines) Up to 1200 x 1200 dpi	
Print technology	Laser; Print resolution technology: 300 dpi, 600 dpi, HP FastRes 1200, HP ProRes 1200	
Print cartridges number	2 (black)	
Standard print languages	HP PCL 6, HP PCL 5 (HP PCL 5 driver available from the Web only), HP postscript level 3 emulation, native PDF printing (v 1.7)	
Printer smart software features	Print preview, duplex printing, print multiple pages per sheet (2, 4, 6, 9, 16), collation, watermarks, store print jobs, easy-access USB	
Printer management / HP SureSupply	UPD Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP JetAdvantage Security Manager/ Yes	
Scan		
Scan type / Technology	Type: Flatbed, ADF (two-sided, single-pass); Technology: CIS (Contact Image Sensor)	
Scan resolution	Hardware: Up to 600 x 600 dpi; Optical: Up to 600 dpi	
Scan file format	PDF, JPEG, TIFF, MTIFF, XPS, PDF/A	Digital Send: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Scan to easy access USB: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Print from easy access USB: PDF, PS, Print Ready files (.prn, .pcl, .cht)
Scan input modes	Front panel applications; Copy, E-mail, Save to Network Folder, Save to USB, Save to Device Memory, Open Extensibility Platform (OXP) applications	
Scan Size	ADF: 8.5 x 14 in Maximum; 4 x 6 in Minimum; Flatbed: 8.5 x 14 in	
Scan speed ¹⁹	Up to 43 ppm/43 ipm (b&w), up to 38 ppm/38 ipm (color) Duplex: Up to 90 ipm (b&w), up to 80 ipm (color)	Up to 45 ppm/64 ipm (b&w), up to 45 ppm/58 ipm (color) Duplex: Up to 136 ipm (b&w), up to 120 ipm (color)
Scanner advanced features	Optimize text/picture; Image adjustments; Job build; Output quality setting; Selectable scan resolution 75 to 600 dpi; Auto detect color; Edge Erase; Job notification; Blank page suppression; HP Quick Sets	Optimize text/picture; Image adjustments; Job build; Output quality setting; Selectable scan resolution 75 to 600 dpi; Auto detect color; Edge Erase; Job notification; Blank page suppression; HP Quick Sets; HP EveryPage; Auto orientation; Embedded Optical Character Recognition (OCR), Auto crop to page; Auto-tone
Bit depth / Grayscale levels	24-bit / 256	
Digital sending standard features	Scan to E-mail; Save-to-Network Folder; Save-to-USB drive; Send to FTP; Send to Internet Fax; Local Address Book; SMTP over SSL; Blank Page Removal; Edge Erase; Auto Color Sense; Auto Crop To Content; Compact PDF	Scan to E-mail; Save-to-Network Folder; Save-to-USB drive; Send to Sharepoint; Send to FTP; Send to LAN Fax; Send to Internet Fax; OCR; Local Address Book; SMTP over SSL; Blank Page Removal; Edge Erase; Auto Color Sense; Auto Crop To Content; Compact PDF; Auto Tonescape; Auto Orientation; Multi-Pick Detect; Auto Straighten; Auto Crop To Page; OCR
Copy		
Copy speed ¹⁸	Black (ISO): Up to 43 cpm; First copy out: As fast as 6.3 sec; As fast as 11.1 sec (100 V) Black; 2-sided: Up to 36 cpm Black	Black (ISO): Up to 43 cpm; First copy out: As fast as 6.2 sec; As fast as 11.3 sec (100 V) Black; 2-sided: Up to 36 cpm Black
Copy resolution	Black (text and graphics): Up to 600 x 600 dpi; Color (text and graphics): Up to 600 x 600 dpi	
Maximum Number of Copies	Up to 9999 copies	
Copier resize	25 to 400%	
Copier settings	Two-sided copying; scalability; image adjustments (darkness, contrast, background cleanup, sharpness); N-up; N or Z-ordering; content orientation; collation; booklet; job build; edge-to-edge job storage; ID Copy; Book Copy; A-to-B Copy (different media sizes)	
Fax		
Fax speed		Up to: 33.6 kbps / Letter: 3 sec per page
Fax resolution		Black (best): Up to 300 x 300 dpi (400 x 400 dpi for received faxes only); Black (standard): 203 x 98 dpi
Fax smart software features		Stored faxes; Fax archiving; Fax forwarding; Scale to fit; Fax address book; LAN/Internet fax; Fax number confirmation; Holiday fax schedule
Fax Features		Fax memory: Up to 500 pages; Auto fax reduction supported: Yes; Auto-redialing: Yes; Fax delayed sending: No; Distinctive ring detection supported: No; Fax forwarding supported: Yes; Fax phone TAM interface supported: No; Fax polling supported: Yes (poll to receive only); Fax telephone mode supported: No; Junk barrier supported: Yes; Maximum speed dialing numbers: Up to 100 numbers (each with 210 destinations); PC interface supported: Yes; Remote retrieval capability supported: No; Telephone handset supported: No
Connectivity		
Standard connectivity	2 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network	1 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network; 1 Fax
Network capabilities	Yes, via built-in Gigabit Ethernet	
Wireless capability	Optional, enabled with purchase of HW accessories.	No
Mobile printing capability	HP ePrint; Apple AirPrint™; Mopria™-certified	
Memory ⁸	Standard: 1.25 GB (Printer), 500 MB (Scanner); Maximum: 2.0 GB (Printer), 500 MB (Scanner)	
Processor speed	1.2 GHz / Storage: Standard, 16 GB SSD / Hard disk: Optional, 500 GB (with accessory B5L29A)	1.2 GHz / Hard disk: Standard, embedded HP High-Performance Secure Hard Disk, minimum 500 GB; AES 128 hardware encryption or greater; Secure erase capabilities (Secure File Erase-Temporary Job Files, Secure Erase-Job Data, Secure ATA Erase-Disk); U.S. Government: Standard, FIPS 140-2 validated hard disk, minimum 500 GB
Duty cycle (monthly) ⁹	Letter: Up to 150,000 pages; Recommended monthly page volume: 2000 to 7500	
Paper handling		
Input	1 x 550-sheet input tray; 1 x 100-sheet multipurpose tray; 3 x optional additional 550-sheet input trays; Up to 650 sheets Standard; Up to 10 envelopes	
Output	Standard: 250-sheet output bin; Up to 250 sheets Standard; Transparencies: Up to 75 sheets	Standard: 250-sheet output bin, convenience stapler; Up to 250 sheets Standard; Transparencies: Up to 75 sheets
Duplex Options	Automatic (standard)	
Auto document feeder capacity	Standard, 100 sheets	
Envelope feeder	No	
Standard paper trays	2	
Media types	Paper (bond, color, letterhead, plain, preprinted, prepunched, recycled, rough); envelopes; labels; cardstock; transparencies; user-defined	
Media weight	Tray 1: 16 to 53 lb; Tray 2: +/- 16 to 32 lb	
Media sizes	Tray 1: Letter, legal, executive, 4 x 6, 5 x 8, 8.5 x 13; envelopes (No. 10, Monarch); Tray 2: letter, legal, executive, 8.5 x 13; Optional trays 3+: letter, legal, executive, 8.5 x 13 in; Optional Automatic Duplexer: letter	
Media Sizes Custom	Tray 1: 3 x 5 to 8.5 x 14 in; 550-sheet input Tray 2: 4.1 x 5.8 to 8.5 x 14 in; optional 550-sheet input Tray 3+: 4.1 x 5.8 to 8.5 x 14 in	
Dimensions (w x d x h)	18.98 x 19.52 x 19.55 in; Maximum: 19.96 x 24.83 x 19.55 in	
Weight ¹	48.2 lb	48.6 lb
What's in the box	HP LaserJet M527 Printer; HP 87A Black Original LaserJet Toner (~ 9000 pages); CDs containing software and electronic documentation; User Guide; Support Flyers; Warranty Cards; Required Erratas	HP LaserJet M527 Printer; Introductory HP Black Original LaserJet Toner Cartridge (~ 6000 pages); CDs containing software and electronic documentation; User Guide; Support Flyers; Warranty Cards; Required Erratas; Fax cable (AP only)
Replacement cartridges ⁵	HP 87A Black Original LaserJet Toner Cartridge (CF287A); HP 87X Black Original LaserJet Toner Cartridge (~18000 pages) CF287X	
Warranty features	One-year, next-business day, onsite warranty. Warranty and support options vary by product, country and local legal requirements. Go to http://www.hp.com/support to learn about HP award winning service and support options in your region.	
Energy efficiency compliance	ENERGY STAR® qualified; CECP; EPEAT® Silver	ENERGY STAR® qualified; EPEAT® Gold; CECP
Control panel	8.0-in (20.3 cm) color LCD with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu)	8.0-in (20.3 cm) color LCD with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu); Integrated keyboard
Display	8.0 in (20.3 cm) touchscreen, SVGA LCD (color graphics), smooth gesture enabled touchscreen	
Software included	For Windows OS: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Send Fax, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), Online user manuals; For Mac OS: Welcome Screen, Directs users to HP.com or OS App Source for LaserJet Software	
Fonts and typefaces	105 internal TrueType fonts; scalable in HP PCL, 92 internal scalable fonts in HP postscript Level 3 emulation (Euro symbol built-in); 1 internal Unicode Fonts (Andale Mono World Type); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria); additional font solutions available via third-party flash memory cards; HP LaserJet Fonts and IPDS Emulation available at http://www.hp.com/go/laserjetfonts	
Compatible operating systems ¹¹	Windows OS compatible with In-Box Driver: Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions; Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows OS compatible with Universal Print Driver (From http://www.hp.com); Windows XP SP3 32- & 64-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32- & 64-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); Mac OS (HP Print Drivers available from http://www.hp.com and Apple Store); OS X 10.8 Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosemite; Mobile OS (In-OS drivers); iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP, SUSE Linux (11.2, 12.3, 13.1), Fedora (17, 18, 19, 20); Linux Mint (13, 14, 15, 16, 17); Boss (3.0, 5.0); Ubuntu (10.04, 11.10, 12.04, 12.10, 13.04, 13.10, 14.04, 14.10); Debian (6.0.x, 7.x); Other OS: UNIX	
Compatible network operating systems	Windows OS compatible with In-Box Driver: Windows Server 2003/2003 R2 32-bit (SP1/SP2) Standard/Enterprise (+ Cluster & Terminal Services); Windows Server 2008 32-/64-bit (SP2) Standard/Enterprise (+ Cluster & Terminal Services); Windows Server 2008 R2 64-bit (SP1) Standard/Enterprise (+ Cluster & Terminal Services); Windows Server 2003/2003 R2 32-/64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services); Windows Server 2008/2008 R2 32-/64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services); Windows Server 2012/2012 R2 64-bit Standard/Foundation/Essentials/Datacenter (+ Cluster & Terminal Services); Citrix (on Windows Server 2003/2003R2); Citrix MetaFrame Presentation Server, 3.0; Citrix MetaFrame XP Presentation Server (Feature Release 1, 2, and 3); Citrix Presentation Server 4.0/4.5; Citrix XenApp 5.0 (Plus Feature Pack 2 & 3); Citrix (on Windows Server 2008/2008R2); Citrix XenApp 5.0 (Plus Feature Pack 2 & 3); Citrix XenApp 6.0/6.5/7.5; Citrix XenDesktop 5.6/7.0/7.5; Citrix (on Windows Server 2012/2012R2); Citrix XenApp 7.5; Citrix XenDesktop 7.0/7.5; Novell Servers (www.novell.com); ovell iPrint Appliance v1.0; Novell Open Enterprise Server 11/SP1; Novell Open Enterprise Server 2 for Linux; NetWare 6.5/SP8; Novell Clients (www.novell.com); Windows 8 (32-bit / 64-bit) recommend v5.86+; 8.1 recommend v5.94+; Windows 7 (32-bit / 64-bit) recommend v5.82+; Windows Vista (32-bit / 64-bit) recommend v5.82+; Windows XP / SP3 (32-bit only) recommend v5.82+; Setup Scan To Folder and Email.	
Minimum system requirements	PC: Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions; Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); CD-ROM or DVD drive, or internet connection; Dedicated USB or network connection or Wireless connection; 200 MB available hard disk space; OS compatible hardware (For OS hardware requirements see http://www.microsoft.com); Mac: Mac OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Internet; USB; 1 GB HD; OS compatible hardware (For OS hardware requirements see http://www.apple.com)	
Power ^{20 21}	Power supply type: Internal (Built-in) power supply; Power supply required: Input Voltage: 100 to 127 VAC, 50/60 Hz, 7.5 A (+/- 10%); Input Voltage: 220 to 240 VAC, 50/60 Hz, 4.0 A (+/- 10%) (Not dual voltage, input voltage requirement and supplied power cord varies by part number and option code identifier); Power consumption: 671 watts (Printing), 27.8 watts (Ready), 3.2 watts (Sleep), 0.71 watts (Auto-Off/Auto-On), LAN connection: 0.06 watts (Auto-Off), 0.06 watts (Off); Best technical electricity consumption (TEC): 1.648 kWh/Week	Power supply type: Internal (Built-in) power supply; Power supply required: Input Voltage: 100 to 127 VAC, 50/60 Hz, 7.5 A (+/- 10%); Input Voltage: 220 to 240 VAC, 50/60 Hz, 4.0 A (+/- 10%) (Not dual voltage, input voltage requirement and supplied power cord varies by part number and option code identifier); Power consumption: 671 watts (Printing), 27.8 watts (Ready), 3.2 watts (Sleep), 0.71 watts (Auto-Off/Auto-On), LAN connection: 0.06 watts (Auto-Off), 0.06 watts (Off); Typical electricity consumption (TEC) number: 1.752 kWh/Week (Energy Star), 1.648 kWh/Week (Blue Angel); Best technical electricity consumption (TEC): 1.648 kWh/Week
Acoustics ⁷	Acoustic power emissions: 6.8 B(A)	
Operating environment	Operating temperature range: 59 to 90.5°F; Recommended operating temperature: 63.5 to 77°F; Storage temperature range: -4 to 140°F; Operating humidity range: 10 to 80% RH; Recommended operating humidity range: 30 to 70% RH	
Security management	Management security: SNMPv3, SSL/TLS, WPA2-Enterprise, 802.1X authentication (EAP-PEAP, EAP-TLS), IPP over TLS, IPsec/Firewall with Certificate, Pre-Shared Key Authentication, and Kerberos Authentication; Support for WPA-10 IPsec Configuration using IPsec Plug-in	

¹ Includes size A toner cartridge.

² AirPrint™ and iOS 4.2 or later devices require an 802.11 wireless network connection to the printer. Wireless performance is dependent upon physical environment and distance from the access point. AirPrint and the AirPrint Logo are trademarks of Apple® Inc. Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>

³ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device.

⁴ Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.

⁵ Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>

⁶ HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit <http://www.hp.com/go/SureSupply>

⁷ Acoustic values are subject to change. For current information see <http://www.hp.com/support>

⁸ Maximum memory is with 1 GB DIMM installed. The maximum the FW can use is 2GB so 250 MB is unused in this configuration.

⁹ Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.

¹⁰ HP recommends that the number of scanned pages per month be within the stated range for optimum device performance.

¹¹ Not all "Compatible Operating Systems" are supported with inbox software; Full solution software available only for Windows 7 and newer; Legacy Windows Operating Systems (XP, Vista, and equivalent servers) get print and Scan drivers only; Windows RT OS for Tablets (32- & 64-bit) uses a simplified HP print driver built into the RT OS; UNIX modelscripts are available on <http://www.HP.com> (Modelscripts are printer drivers for UNIX operating systems); Linux systems use in-OS HPLIP software.

¹² Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

¹³ Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

¹⁴ Measured using ISO/IEC 17629. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the input voltage, system configuration, software application, driver, and document complexity.

¹⁵ First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

¹⁶ Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.

¹⁷ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.

To learn more, visit hp.com

© Copyright 2017–2019 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.

4AA6-2586ENL, October 2019, R3

